



VHF AND UHF TRANSCEIVERS

IC-F16

(VHF transceiver, rotary type)

IC-F16S

(VHF transceiver, toggle type)

IC-F26

(UHF transceiver, rotary type)

IC-F26S

(UHF transceiver, toggle type)

Built to last, built to work!

- Tough and reliable construction
- Simple operation
- Wide range frequency coverage
- Lithium-ion battery standard
- Built-in CTCSS and DTCS
- Multiple 2-Tone, Multiple 5-Tone
- Optional voice scrambler, man down and DTMF decoder units
- Wide range of accessories available



Icom Inc.

Built to last, built to work!



The IC-F16/S series shows Icom's sign. Simple operation for every tool for your daily business. Its resistant to shock and vibration. The locks the battery pack to the radio, Li-Ion battery pack, loud and clear and option unit connector combinations.



Tough and reliable construction

The IC-F16/S series is built around an aluminum die-cast chassis and covered with tough polycarbonate casing. This radio is built to last. Its dual slide rail securely locks the battery to the radio. The battery terminal is covered with a non-corrosive rubber packing. The belt clip is clamped between the radio and the battery, making it nearly impossible to knock loose.

Simple operation

Having only 3 buttons, volume and channel knobs, the IC-F16/S series does not require special training to use. Positive button action for sure operation even when wearing gloves, allows you to get down to the business of communicating without fuss.

Wide frequency coverage

The IC-F16/S series covers a wide frequency range with one version (136–174, 400–470MHz). Wide and narrow channel spacing (25, 12.5kHz) is programmable per channel.

VHF TRANSCEIVERS

IC-F16

IC-F16S

UHF TRANSCEIVERS

IC-F26

IC-F26S



s new direction in LMR radio de-
 scription but a powerful and reliable
 very durable construction is re-
 e dual rail guide design securely
 dio. Wide range frequency cover-
 d clear audio, built-in signalings
 oined with Icom grade electrical
 will easily exceed your expecta-

Long use even in extreme cold
 Supplied 2300mAh (typ.) Li-Ion battery pack, BP-232H has superior electro-chemical characteristics even in extremely cold areas (0°C to -30°C). It provides stable output for longer while having less voltage reduction at low temperatures.

Optional board
 The IC-F16/S series has an expansion socket for adding an optional board. Voice scrambler, man down and DTMF decoder features are available, depending on the installed board.

Most popular signalings built-in
 Use the built-in 2-Tone, 5-Tone, CTCSS and DTCS capabilities as standard to set up your own talk groups and quiet standby when others are talking.

Multiple 2-Tone, Multiple 5-Tone
 Up to ten 2-Tone/eight 5-Tone codes can be decoded on a channel. When a matched tone is received, the following items are programmable for each code.

- Beep sound
- Answer back
- Stun
- LED blink
- Scan

Other features

- MDC PTT ID and MDC emergency call functions are available (Transmit only)
- LED low battery alert
- TOT function and lock out penalty timer
- 2 step power saver
- Normal and priority scan
- 500mW loud and clear audio
- Optional VOX headset
- PC programming capability
- Embedded ESN (Electronic serial number)

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.

BATTERY PACKS AND CASE

▲ BP-230N ▲ BP-232H ▲ BP-240

Battery packs	Type	Capacity	Operating time*	Output power (VHF/UHF)
BP-230N	Li-Ion, 7.4V	950mAh (min.) 980mAh (typ.)	9 hours	5W/4W
BP-232H	Li-Ion, 7.4V	2250mAh (min.) 2300mAh (typ.)	21 hours	5W/4W
BP-240	AAA (LR03) batteries x 6		-	1W

* Operating time is approximate time (at 20°C). Tx: standby=5:5:90. Power save on.

REGULAR CHARGER

▲ BC-171
▲ BC-147SE

BC-171 DESKTOP CHARGER + BC-147SE AC ADAPTER
 Charges the BP-232H in 10 hours (approx.).

RAPID CHARGER

▲ BC-160
▲ BC-123SE

BC-160 DESKTOP CHARGER + BC-123SE AC ADAPTER
 Charges the BP-232H in 3 hours (approx.).
BC-119N + AD-106 + BC-145SE is also available. : Charges the BP-232H in 3 hours (approx.).

POWER SUPPLY CABLES

▲ CP-17L ▲ OPC-515L

CP-17L CIGARETTE LIGHTER CABLE, OPC-515L DC POWER CABLE
 For use with the BC-160 or BC-119N. (12-16V DC required).

MULTI-CHARGER

▲ BC-121N+AD-106 (6 pcs.) ▲ OPC-656 ▲ BC-157

BC-121N MULTI-CHARGER + BC-157 AC ADAPTER
 Rapidly charges up to 6 battery packs (Six AD-106s are required). Charges the BP-232H in 3 hours (approx.).
OPC-656 DC POWER CABLE : For use with the BC-121N. (12-20V DC required).
BC-121N + AD-106 + BC-157S is also available.

BELT CLIPS AND LEATHER BELT HANGERS

▲ MB-93 ▲ MB-96F

MB-93 : Swivel type belt clip.
MB-94 : Alligator type. Same as supplied.
MB-96N : Swivel type belt hanger.
MB-96F : Fixed type belt hanger.
MB-96FL : Long type belt hanger.

HEADSETS and PTT/VOX UNIT

▲ HS-94 ▲ HS-95 ▲ HS-97 ▲ VS-1L

HS-94: Earhook headset with flexible boom microphone.
HS-95: Behind-the-head headset with flexible boom microphone.
HS-97: Throat microphone fits around your neck and picks up speech vibration.
VS-1L: PTT/VOX unit. Required when using these headsets with the transceiver.

SPEAKER-MICROPHONES

▲ HM-153L ▲ HM-158L ▲ HM-159L ▲ HM-166L

HM-153L : Durable earphone-microphone with revolving clip.
HM-158L : Compact and durable body with plug screw connector.
HM-159L : Full size durable speaker microphone.
HM-166L : Light-weight earphone microphone with revolving clip.
SP-13 : EARPHONE Provides clear audio in noisy environments.

INTERNAL UNITS

UT-108 DTMF DECODER UT-109 VOICE SCRAMBLER UNIT UT-110 VOICE SCRAMBLER UNIT UT-124 MAN DOWN UNIT

UT-108: Provides DTMF decoder capabilities.
UT-109 (#01): Up to 32 scrambling codes are available.
UT-110 (#01): Up to 1020 scrambling codes are available.
UT-124: Automatically sends an emergency signal when the transceiver is left in a horizontal position for a preset time.

CHARGER BRACKET

MB-130

MB-130: Vehicle charger bracket for use with BC-160.

STUBBY ANTENNAS

- FA-SC56VS : 150-162MHz
- FA-SC57VS : 160-174MHz
- FA-SC73US : 450-490MHz

CUT ANTENNAS

- FA-SC61VC : 136-174MHz
- FA-SC61UC : 380-520MHz

Cut the antenna element to tune to a specific center frequency.

ANTENNAS

- FA-SC25V : 136-150MHz
- FA-SC55V : 150-174MHz
- FA-SC25U : 400-430MHz
- FA-SC57U : 430-470MHz

SPECIFICATIONS

GENERAL

- Frequency range :
 - IC-F16/IC-F16S 136–174MHz
 - IC-F26/IC-F26S 400–470MHz
- Number of channels : 16 (IC-F16, IC-F26)
4 (Max., IC-F16S, IC-F26S)
- Channel spacing : 12.5kHz/25kHz
- PLL channel step : 2.5kHz, 3.125kHz (VHF)
5kHz, 6.25kHz (UHF)
- Power supply requirement : 7.2V DC
- Current drain (at 7.2V DC; approx.):

Transmit	VHF (5W)	1.5A
	UHF (4W)	1.6A
Receive	stand-by	70mA
	rated output	300mA
- Antenna impedance : 50Ω
- Usable temperature range : –30°C to +60°C
- Dimensions (with BP-232H) : 53 (W) × 120 (H) × 42.4 (D) mm
(projections are not included)
- Weight : 296g (approx. with BP-232H)

TRANSMITTER

- Output power : 5W (VHF), 4W (UHF)
- Max. frequency deviation : ±5kHz (Wide)
±2.5kHz (Narrow)
- Frequency error : ±2.5ppm
- Spurious emissions : 80dB typ.
- Adjacent channel power :
 - VHF 80/70dB typ. (Wide/narrow)
 - UHF 75/68dB typ. (Wide/narrow)
- FM Hum and Noise : 46dB typ. (Wide)
40dB typ. (Narrow)
- Audio harmonic distortion : 3% typ. (AF 1kHz, 40% deviation)
- Modulation limiting : 60–100% of max. deviation
- External microphone connector :
3-conductor 2.5 (d) mm /2.2kΩ

Measurements made in accordance with EIA/TIA-603. All stated specifications are subject to change without notice or obligation.

RECEIVER

- Sensitivity : 0.25μV typ. (at 12dB SINAD)
- Squelch sensitivity : 0.25μV typ. (at threshold)
- Adjacent channel selectivity : 75dB typ. (Wide)
65dB typ. (Narrow)
- Spurious response : 70dB
- Intermodulation : 74dB typ.
- Hum and noise ratio : 50dB typ. (Wide)
45dB typ. (Narrow)
- Audio output power : 500mW typ.
(at 5% distortion with an 8Ω load)
- External speaker connector : 2-conductor 3.5 (d) mm/8Ω

Applicable U.S. Military Specifications

Icom makes rugged products that have been tested to and passed the following MIL-STD requirements and strict environmental standards.

Standard	MIL 810F	
	Method	Procedure
Low Pressure	500.4	I, II
High Temperature	501.4	I, II
Low Temperature	502.4	I, II
Temperature Shock	503.4	I
Solar Radiation	505.4	I
Rain Blowing/Drip	506.4	I, III
Humidity	507.4	–
Salt Fog	509.4	–
Dust Blowing	510.4	I
Vibration	514.5	I
Shock	516.5	I, IV

Also meets equivalent MIL-STD-810-C, -D and -E.

SUPPLIED ACCESSORIES

(May differ according to version)



Icom, Icom Inc. and Icom logo are registered trademarks of Icom Incorporated (Japan) in Japan, the United States, the United Kingdom, Germany, France, Spain, Russia, Australia, New Zealand and/or other countries.

Icom Inc. 1-1-32, Kami-minami, Hirano-Ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

www.icom.co.jp/world

Count on us!

Icom America Inc.

12421 Willows Road NE,
Kirkland, WA 98034, U.S.A.
Phone: +1 (425) 454-8155
Fax: +1 (425) 454-1509
E-mail: sales@icomamerica.com
URL: <http://www.icomamerica.com>

Icom Canada

Glenwood Centre #150-6165
Highway 17A, Delta, B.C.,
V4K 5B8, Canada
Phone: +1 (604) 952-4266
Fax: +1 (604) 952-0090
E-mail: info@icomcanada.com
URL: <http://www.icomcanada.com>

Icom Brazil

Rua Itororó, 444 Padre Eustáquio
Belo Horizonte MG,
CEP: 30720-450, Brazil
Phone: +55 (31) 3582 8847
Fax: +55 (31) 3582 8987
E-mail: sales@icombrasil.com

Icom (Europe) GmbH

Communication Equipment
Auf der Krautweide 24
65812 Bad Soden am Taunus, Germany
Phone: +49 (6196) 76685-0
Fax: +49 (6196) 76685-50
E-mail: info@icom-europe.com
URL: <http://www.icomeurope.com>

Icom Spain S.L.

Ctra. Rubí, No. 88 "Edificio Can Castanyer"
Bajos A 08174, Sant Cugat del Valles,
Barcelona, Spain
Phone: +34 (93) 590 26 70
Fax: +34 (93) 589 04 46
E-mail: icom@icomspain.com
URL: <http://www.icomspain.com>

Icom (UK) Ltd.

Blacksole House, Altira Park,
Herne Bay, Kent, CT6 6GZ, U.K.
Phone: +44 (0) 1227 741741
Fax: +44 (0) 1227 741742
E-mail: info@icomuk.co.uk
URL: <http://www.icomuk.co.uk>

Icom France s.a.s.

Zac de la Plaine,
1 Rue Brindejone des Moulinais, BP 45804,
31505 Toulouse Cedex 5, France
Phone: +33 (5) 61 36 03 03
Fax: +33 (5) 61 36 03 00
E-mail: icom@icom-france.com
URL: <http://www.icom-france.com>

Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road,
Clayton, VIC 3168 Australia
Phone: +61 (03) 9549 7500
Fax: +61 (03) 9549 7505
E-mail: sales@icom.net.au
URL: <http://www.icom.net.au>

Icom New Zealand

39C Rennie Drive, Airport Oaks,
Auckland, New Zealand
Phone: +64 (09) 274 4062
Fax: +64 (09) 274 4708
E-mail: inquiries@icom.co.nz
URL: <http://www.icom.co.nz>

Asia Icom Inc.

6F No.68, Sec. 1 Cheng-Teh Road,
Taipei, Taiwan, R.O.C.
Phone: +886 (02) 2559 1899
Fax: +886 (02) 2559 1874
E-mail: sales@asia-icom.com
URL: <http://www.asia-icom.com>

Shanghai Icom Ltd.

No.101, Building 9, Caifuxingyuan Park,
No.188 Maoting Road, Chedun Town,
Songjiang District, Shanghai, 201611, China
Phone: +86 (021) 6153 2768
Fax: +86 (021) 5765 9987
E-mail: bjicom@bjicom.com
URL: <http://www.bjicom.com>

Your local distributor/dealer: