

INSTRUCTIONS

MKR - 2

1. Check parts contents. (See figure 1.)
2. If the MKR-2 is to be used for 2 meter operation, no cutting of the radials is required. For 220MHz. operation, cut nine (9) inches from the straight end of the radial with a hacksaw leaving ten (10) inches from the cut tip to bend. Deburr the edges with a file.
3. Push on the three (3) plastic end tips to the radial ends.
4. Place one lockwasher 2235-15 on insulator 6406 and insert through plate 4717-1 and bracket 2902-6. Use another lockwasher 2235-15 under the blanket and install nut 4317. Use the three (3) sets of screws 5180-1 and nuts (2382-1) plus lock washer (2381-10) to secure the plate to the bracket. Do not tighten.
5. Using the "U" bolt (3488-4) temporarily mount the assembly to a stationary vertical support for convenience in attaching radials.
6. Install the radials between the plate and the bracket as shown in Figure 2. Tighten the three screws (3) to hold radials in place.
7. Attach the coax cable (50 ohm) using a PL-259 connector and seal with Krylon, Liquid Tape or Silicone if intended for outside use.
8. Attach any 2 meter (or 220 MHz.) antenna with 3/8 - 24 thread. For indoor use, set on floor or wooden table and check SWR, tune antenna if necessary. The radials for either 2 meter or 220 MHz. are sufficiently broad to eliminate tuning over the entire band(s).

NEWTRONICS ANTENNA CORP. LIMITED WARRANTY

Newtronics Inc. warrants its products to be free of defects in material and workmanship and extends this warranty under intended use and normal service conditions to the original owner for a period of one year from the date of purchase.

This warranty does not apply to any product that has been repaired or altered in any manner and is void for any damage due to accident, neglect, unreasonable use, improper installation or any other cause not arising out of defects in material or workmanship.

The obligations of Newtronics Inc. are limited to repairing or replacing, at its option, any product or part that is returned to the factory all transportation charges prepaid, accompanied by proof of purchase and which examination reveals to have been defective within the warranty period stated above. Newtronics Inc. does not assume, nor is any person authorized to assume for it, any obligation other than that herein stated.

Any implied warranties, including but not limited to fitness for a particular purpose, are limited in duration for the above one year period.

Newtronics Inc. shall not be liable under this warranty, or any implied warranty, for loss of the product or for other consequential loss of damage incurred by the purchaser.

Some states do not allow the exclusion of limitation of implied warranties of consequential damages and so the above exclusions of limitations may not apply. This warranty gives you special legal rights and you may have other rights that vary from state to state.

Kit No. 6409

6410




Rev. 3, 9/92

Newtronics Antenna Corp.
Mineral Wells, Texas 76067

Printed in U.S.A.

MKR-2



Kit No. 6409