

ICOM

144 MHz FM TRANSCEIVER

UHF FM TRANSCEIVER

IC-T22A

(144 MHz U.S.A. version)

IC-T42A

(440 MHz U.S.A. version)

IC-T22E

(144 MHz Europe version)

IC-T42E

(430 MHz Europe version)

Meets
MIL-STD 810



The IC-T22A/E and IC-T42A/E are mono band handhelds packed with features you would expect to find in a handheld twice the size. From alphanumeric display to the new microphone simple remote control function these handhelds utilize the latest in Icom technology. And they look great!

High performance that easily fits in your hand

With slim dimensions of 57(W) x 110(H) x 27(D) mm*, including BP-171, these handhelds fit comfortably in the palm of your hand—carry them around in your shirt pocket or a small bag. However, there is nothing small about their performance.

*U.S.A. version with BP-180: 2 $\frac{1}{4}$ (W) x 4 $\frac{13}{16}$ (H) x 1 $\frac{1}{8}$ (D) in.

Alphanumeric memory channels

Available memory channels are expandable from 40 to 80* (not including scan edges and call channel) and channels can be tagged with a 6-character alphanumeric name such as a call sign, repeater name, etc. for operating convenience. Nothing is more frustrating than losing all your channel information when your battery goes dead. EE-PROM memory backup ensures that this won't happen. Now you have memory to memory transfer for convenient memory management.

*Memory names cannot be used when memories are expanded to 80.

Alphanumeric message pager

5 transmit and 5 receive message memories are available independently from regular memory channels allowing you to use the transceiver as a simple message pager (up to six characters per message). This paging function is compatible with the paging functions for other Icom handhelds and mobiles.

Microphone simple remote control function

This new function allows you to change the default functions of the optional HM-75A's switches: squelch monitor, call channel, memory channel 1 and memory channel 2. Doing so makes operation via the HM-75A simple for driving, hiking—especially convenient for group operation.

And more...

- MOS-FET power module
- Accepts 4.5 to 16 V external DC power supply
- log memory and repeater memory for auto storage of the last-transmitted frequencies
- 50 frequency CTCSS tone encoder (optional for Europe and Italy versions)
- 5 DTMF (30 digits each) memories for auto dialing
- Numerous scans available
- LCD backlighting for easy night operation
- An antenna, battery pack* and battery charger* are included with the transceiver.

*Some versions include a battery case instead of these.

IC-T42E

IC-T22A

Icom Inc.

SPECIFICATIONS

GENERAL

- Frequency coverage : (Unit: MHz)

Version	IC-T22A/E	IC-T42A/E
U.S.A.	Tx: 144-148 Rx: 136-174**	Tx: 440-450 Rx: 400-470**
Europe	144-148	430-440
Asia	Tx: 144-148 Rx: 140-150**	430-440
Italy	Tx: 144-148 Rx: 136-174**	Tx: 430-440 Rx: 400-470**

Guaranteed range (MHz): **144-148, **440-450, **430-440

- Mode : FM
- Acceptable power supply : 4.5 to 16 V DC
- Number of memory channels: 87 (max.)
- Tuning steps (kHz) : 5, 10, 12.5, 15, 20, 25, 30 or 50
- Dial select steps : 100 kHz or 1 MHz
- Usable temperature range : -10°C to +60°C (+14°F to +140°F)

- Current drain (at 13.5 V, typical):

Transmit	High	1.4 A
	Low	500 mA
Receive	Rated audio	150 mA
	Power saved	15 mA (average)

- Dimensions (with BP-171) : 57(W) x 110(H) x 27(D)
(with BP-180) : 2½(W) x 4½(H) x 1¼(D)

- Weight (w/BP-171 and antenna) :
IC-T22A/E : 310 g (10.9 oz)
IC-T42A/E : 300 g (10.6 oz)

TRANSMITTER

- Output power (at 13.5 or 9.6 V) : 5 W or 500 mW (approx.) (at 7.2 V) : 3.5 W or 500 mW
- Modulation system : Variable reactance frequency modulation
- Max. frequency deviation : ±5.0 kHz
- Spurious emissions : Less than -60 dB
- Microphone impedance : 2 kΩ

RECEIVER

- Receive system : Double conversion superheterodyne
- Intermediate frequencies : 1st : 30.85 MHz
2nd : 450 kHz
- Sensitivity (typical) : Less than 0.16 µV
- Squelch sensitivity (at threshold) : Less than 0.16 µV
- Spurious and image rejection:
IC-T22A/E : Less than -60 dB
IC-T42A/E : Less than -50 dB
(Except ½ of image freq.)
- Audio output power : More than 200 mW (10% at 13.5 V) ; distortion with an 8 Ω load
- Audio output impedance : 8 Ω

The IC-T22A/E meet MIL-STD requirements and strict environmental standards for shock (MIL 810C, D, E) and vibration (MIL 810 C, D, E).

All stated specifications are subject to change without notice or obligation.

OPTIONS

BATTERY PACKS AND CASE

BP-171

4.5 V, 700 mAh
BP-172
4.8 V, 950 mAh



BP-173

9.6 V, 850 mAh
BP-180
7.2 V, 600 mAh



BP-170

18 (AA)
batteries x 4



Approx. output powers and operating times at 25°C. Tx: 10 min power; Rx: Standby x 1 : 1 hr

	BP-171	BP-172	BP-173	BP-180
IC-T22A/E	1.5 W/6h	1.5 W/8h	5 W/3h 20m	3.5 W/4h
IC-T42A/E	1.3 W/4h 30m	1.3 W/6h 10m	5 W/2h 20m	3.5 W/3h 30m

BC-119 DESKTOP CHARGER + AD-56 DESKTOP CHARGER ADAPTER



Rapidly charges battery packs BP-171, BP-172, BP-173 or BP-180. Both AC and DC can be used to power the charger. Some BC-119 versions require the AD-56 additional.

CP-12L CIGARETTE LIGHTER CABLE WITH NOISE FILTER OPC-254L DC POWER CABLE



Allows you to operate the transceiver through a 12 V cigarette lighter socket or 4.5 to 16 V external DC power supply with the CP-12L or OPC-254L, respectively. The connected battery pack is charged simultaneously (12 to 16 V DC necessary).

MB-30 MOBILE MOUNTING BRACKET



For mounting the transceiver on the inside door panel of a vehicle.

SPEAKER-MICROPHONES



HM-46: Compact/light weight. Equipped with an earphone jack.
HM-54: Durable full-sized speaker-microphone.
HM-75A: Allows you to remotely select memory channels, operating frequency, etc.

HS-85 HEADSET



Allows you hands-free operation. Includes VOX, PTT, tone touch, PTT (TOT). Low voltage type.

SP-13 EARPHONE



Provides clear audio in noisy environments.

UT-94 TONE SQUELCH UNIT



Provides tone squelch, pocket beep and tone scan functions.

WALL CHARGER

BC-110A/C/D/V

Regularly charge battery packs. The same as supplied with some versions.

CARRYING CASES

LC-125

For use with the BP-170, BP-171 or BP-172.

LC-126

For use with the BP-173 or BP-180.

Icom Inc.

6-9-16, Kamihigashi, Hirano-ku, Osaka 547-0002, Japan Phone: 06 6793 5302 Fax: 06 6793 0013 URL: <http://www.icom.co.jp/world/index.html>

Count on us!

Icom America Inc.

<Corporate Headquarters>
2380 116th Avenue N.E., Bellevue, WA 98004, U.S.A.
Phone: (425) 454-8155 Fax: (425) 454-1509
URL : <http://www.icomamerica.com>
<Customer Service>
Phone: (425) 454-7619

Icom Canada

3071 #5 Road, Unit 9, Richmond, B.C., V6X 2T4, Canada
Phone: (604) 273-7400 Fax: (604) 273-1900
URL : <http://www.icomcanada.com>

Icom (Australia) Pty. Ltd.

A.C.N. 006 092 575
290-294 Albert Street, Brunswick, Victoria, 3056, Australia
Phone: 03 9387 0666 Fax: 03 9387 0022
URL : <http://www.icom.net.au>

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road, Taipei, Taiwan, R.O.C.
Phone: (02) 2559 1899 Fax: (02) 2559 1874

Icom (Europe) GmbH

Communication Equipment
Himmelgeister Str. 100, D-40225 Düsseldorf, Germany
Phone: 0211 346047 Fax: 0211 333639
URL : <http://www.icomeurope.com>

Icom Spain S.L.

Ctra. de Gracia a Manresa Km. 14,750
08190 Sant Cugat del Valles Barcelona, SPAIN
Phone: (93) 590 26 70 Fax: (93) 589 04 46
URL : <http://www.icomspain.com>

Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay, Kent, CT6 8LD, U.K.
Phone: 01227 741741 Fax: 01227 741742
URL : <http://www.icomuk.co.uk>

Icom France S.a

Zac de la Plaine, Rue Brindejonc des Moulinais
BP 5804, 31505 Toulouse Cedex, France
Phone: 561 36 03 03 Fax: 561 36 03 00
URL : <http://www.icom-france.com>



Certificate Number 014190

Icom Inc. (Japan), is an ISO9001 certification acquired company.

Your local distributor/dealer: