


 **KENWOOD**

ANTENNA TUNER

AT-200




ANTENNA TUNER
AT-200
\$1,499.00

The AT-200 is KENWOOD's antenna tuner which includes functional features such as a through line wattmeter, SWR meter and antenna selector switch.

The AT-200 reduces the clutter in most ham shacks and greatly adds to the effectiveness of your station.

FEATURES

- The AT-200 is an antenna tuner designed for use with the TS-520S and TS-820 series, although it is compatible with most of today's HF transceivers.
- The AT-200 consists of an antenna coupler, a through-line RF wattmeter, an SWR meter and an antenna switch.
- The AT-200 is designed to be used on the amateur bands between 1.8 MHz and 29.7 MHz.
- The RF wattmeter has two ranges, 20 W and 200 W.
- The antenna switch has four outputs. Two of these are for coaxial fed antennas, one is for a wire antenna and one is for connecting a dummy load.
- The AT-200 is also capable of matching your transceiver with a wire antenna such as an inverted-L. This makes it possible to enjoy communication on the lower frequency bands.

SPECIFICATIONS
ANTENNA COUPLER

Frequency range 6 amateur bands from 1.8 to 29.7 MHz
 Input impedance 50 ohms
 Output impedance 50 to 500 ohms, unbalanced
 Through power 200 watts max.

WATTMETER

Type Through-line wattmeter
 Frequency range 1.8 to 29.7 MHz
 Measurable RF power Up to 20/200 watts, switched
 Kinds of RF power Forward and reflected power, switched
 Impedance 50 ohms
 Accuracy Better than $\pm 10\%$ of full scale

SWR METER

SWR detection Toroidal core directional coupler
 Measurable range 1.1 to 10
 Min. power required 4 watts

GENERAL

Connectors, INPUT UHF type, 50 ohms
 Connectors, ANT-1 UHF type
 ANT-2 UHF type
 ANT-3 Wire antenna only
 GND
 Dimensions 6-17/32 (166)W x 6 (153)H x
 7-1/2 (190)D inch (mm)
 Net weight 6.2 lbs. (2.8 kg) approx.