




MODEL R-5 ALLWAVE RECEIVER



DIVISION OF

AEROTRON, INC. - RALEIGH, NORTH CAROLINA



OPERATION

STANDARD AM BROADCAST BAND

CONTROL

Set the controls as follows:

POWER-OFF AM-CW OFF-ANL RAND VOLUME RF GAIN

BANDSPREAD

SETTING

*POWER AM OFF BAND D or E 9 o'clock position Maximum clockwise position

Using the main tuning knob, tune to the frequency of the station desired, on the main dial.

Adjust the VOLUME control as desired.

When tuning signals where the stations are very close together, the main tuning dial can be left at a slightly higher frequency and the fine tuning can be done with the BANDSPREAD control.

*(The dial lights should go on)

SHORT WAVE TUNING

Short Wave Broadcast Stations:

Set the controls for AM Broadcast.

Select the short wave band desired with the BAND switch.

On the short wave bands, all stations are close together, therefore the main dial is used for coarse tuning, to a point slightly higher than the frequency desired. Then use the BANDSPREAD control for fine tuning. Always return the BANDSPREAD control to CAL when using the main tuning dial.

When there is noise on the signal, shift the OFF-ANL switch to ANL. Many kinds of noise will be reduced considerably when the Automatic Noise Limiter is used.

CW TUNING

To tune in a CW signal use the following procedure:

- 1. With the AM-CW switch in AM position, tune the main tuning control until a steady signal is found.
- Turn the RF GAIN control to the lowest possible point while still retaining an audible signal. The VOLUME control should be at midretaining an audible signal, point of its range.
- 3. Tune in the signal with the BANDSPREAD control.
- 4. Put the AM-CW switch in CW position and adjust the BFO TUNING for zero beat.

- Retune the signal with either the main tuning control or the BAND-SPREAD control, and adjust the RF GAIN control for the volume you
- 6. When you want to tune in another CW signal use the main or BAND-SPREAD tuning and RF GAIN controls.

SINGLE SIDEBAND TUNING

Use the procedure given above.

Tune the BANDSPREAD dial very slowly until the voice being received sounds most natural.

Keep the RF GAIN control as low as possible.

FM TUNING

Use the procedure given for AM tuning.

the signal is tuned in exactly on frequency, it will probably not be as clear as you desire.

Tune the radio slightly to one side of the exact frequency, and the voice will become clear and easily understood.

As a general rule, one side will be the clearest, so tune both sides of the frequency to achieve the best response.

LISTENING TO SHORT WAVE

As you become more experienced in using your R5 receiver, you will notice that many foreign stations announce in meters, rather than megahertz. Much of the amateur literature will speak of the 80 meter band, or the 40 meter band, or any of various other widely used frequencies, in meters rather than megahertz.

The formula given below may be used in converting meters to megahertz or megahertz to meters.

300/Megahertz = Meters

For Example:

300/12 MHz = 2512 MHz = 25 meters

or

From meter to megahertz: 300/meters = megahertz

For example: 25 meters

300/25 = 12 MHz

Some interesting possibilities for your short wave listening are listed below:

Amateur Radio - Assigned bands between 1.800 MHz to 54 MHz.

Short Wave Broadcasting - Check with a good reference book regarding frequencies used by various countries.

Citizens Band - Frequencies assigned to private citizens in the United States and several other countries - 26.965 to 27.255 MHz.


Military Communications - Heard over the entire short wave frequency range.

Police, Fire and Commercial - Between 30 and 50 MHz.

LISTENING TO THE FM BAND

Certain bands of frequencies in the 30 - 50 MHz range are allocated by the U. S. Government to what is known as the Public Service Channels. This includes police, fire departments, forestry and conservation, and special emergency service. Frequency modulation is used by these services because of its ability to overcome much of the effect of ignition noises.

In order to enter this exciting world of emergency communications, it will be necessary to use more rigorous standards in the selection of an antenna. It is recommended that the beginner refer to some standard book on the subject, such as the ARRL Antenna Handbook by the AMERICAN RADIO RELAY LEAGUE.



PRINTED CIRCUIT BOARD OUTLINE

AVERAGE GAIN MEASUREMENTS AT 455 KHz

AC line voltage - 117 volts.

Signal Generator with 50 ohm output impedance.

Modulated 30% at 400 Hz.

0.1 uf in series with signal generator output for DC isolation.

Output measured across 3.2 ohm resistor connected to PHONES jack with AC voltmeter. 1.0 volt RMS reference output.

AGC disabled by shorting terminals 2 and 3 on S 102A.

Oscillator disabled by shorting front section of main tuning capacitor, C 102B.

VOLUME at maximum ANL switch OFF BAND on E RF GAIN at maximum AM-CW switch on AM.

APPROXIMATE MICROVOLTS INPUT:	. INPUT TO:	NOTES:
10	Q 1 Base	With C 113 disconnected from bandswitch.
400	Q 1 Collector	I t
22	Q 2 Emitter	O O
1,000	Q 2 Collector	11
55	Q 4 Base	Short T3, terminals 4 & 5
600	Q 4 Collector	Short T3, terminals 4 & 5
400	Q 5 Emitter	Short T3, terminals 4 & 5
0.9 volts	Q 5 Collector	RF GAIN at Minimum
32,000	CR 3 Cathode	RF GAIN at Minimum

GLOSSARY OF TERMS

AM - Amplitude Modulation

ANL - Automatic Noise Limiter

ANT - Antenna

AVC - Automatic Volume Control. Also, called AGC - Automatic Gain Control

BFO - Beat Frequency Oscillator

CQ - A general call used to establish contact between amateurs

CW - Continuous wave. Unmodulated signal with the message transmitted by interruptions which produce dots and dashes.

FM - Frequency modulation

QRM - Interference from other signals

QRX - Standby

QRN - Interference from static

OSO - Contact between two stations.

QSY - Change operating frequency

RF GAIN - Controls the sensitivity of the RF and/or IF amplifier stages.

RST - Readability, Signal Strength, Tone

SWL - Short wave listener

STATIONS FOR INTERNATIONAL LISTENING

There are many radio stations throughout the world which broadcast in English on the short wave frequencies. Some of these stations can be found by "scanning" the appropriate bands on your R5 receiver. For a comprehensive listing, refer to WORLD RADIO-TV HANDBOOK, or any one of the directories available. The list below will serve as a starting point in your enjoyment of this fascinating hobby.

COUNTRY	CITY	FREQUENCY In Megahertz
Albania	Tirana	7.265
Argentina	Buenos Aires	9.690
Australia	Melbourne	15.220-17.840
Bulgaria	Sofia	6.070
China	Peking	1.506-17.680
Cuba	Havana	6.170-11.760
Czechos lovak i a	Prague	5.930-7.115-6.345
Denmark	Copenhagen	9.520
Ecuador	Quito	9.745-11.915-15.115
England	London	6.195-7.130-9.510-11.780
Germany	Berlin	5.960-6.160 -9 730
Ghana	Accra	6,110
Hol land	Hilversum	11.730
Hungary	Budapest	6.235-9.833
Italy	Rome	6.010-9.630
Japan	Tokyo	11.780-15.135
Lebanon	Beirut	9.710
Netherlands Antilles	Bona i re	9.605
Portugal	Lisbon	6.025-6.185
Roumania	Bucharest	5.990-9.570
South Africa	Johannesburg	9.675-11.880
Spain	Madrid	6.130-9.760
Sweden	Stockholm	5.990
Switzerland	8erne	5.965-6.120-9.535
U. A. R.	Cairo	9.475
U.S.S.R.	Kiev	7.120-7.310-9.665
U.S.S.R.	Moscow	7.150-7.205-7.310-9.665
Vatican	Vatican City	5.985-7.250

FOR MORE INFORMATION --

There are many sources you can go to for more extensive information concerning short wave radio. Some standard references which offer a wealth of information are listed below:

AMERICAN RADIO RELAY LEAGUE, INC. Newington, Conn. 06111

WORLD RADIO TV HANDBOOK


The largest organization of radio amateurs.


List of all radio and television stations throughout the world. Can be ordered from:

Gilfer Associates P. O. Box 238 Park Ridge, New Jersey, 07656


Published in the magazine RADIO-TV EXPERI-MENTER. Any three consecutive issues contain a complete issue of the log.

WHITE'S RADIO LOG







ALIGNMENT




STEP	SIGNAL GENERATOR CONNECTIONS	GENERATOR PREQUENCY	SE SE
1.	High side through a .01 mfd capa- citor to stator plates of rear section of TUNING capacitor.	455 XHz (30% mod.)	
2.	High side through a .01 mfd capa- citor to stator plates of rear section of tuning capacitor. Ho- dulation OFF.	455 KRz	
3.	High side through EIA entenna to ANT terminal on rear of chassis. Low side to chassis	1.3 MHz (30% mod.)	






ALIGNMENT



STEP	SIGNAL GENERATOR CONNECTIONS	GENERATOR PREQUENCY	SI SI
1.	High side through a .01 mfd capa- citor to stator plates of rear section of TUNING capacitor.	455 KHz (30% mod.)	
2.	High side through a .01 mfd capa- citor to stator plates of rear section of tuning capacitor. Mo- dulation OFF.	455 KHz	
3.	High side through EIA antenna to ANT terminal on rear of chassis. Low side to chassis	1.3 MHz (30% mod.)	




NT PROCEDURE

ALIGNMENT PROCEDURE

Use an amplitude modulated generator covering 455 KHz to 54 MHz.
Connect the output meter across the speaker voice coil.
Use non-meetallic alignment tools. CC #8606L or similar.
Use a standard ElA dummy antenna as shown.
VOLUME control near maximum clockwise.
BANDSPMEAD control at 10.
AM-CV waitch at AM
OFF-AML switch in OFF position.
RF-GAMI at maximum unless noise exceeds 50 milliwatts with no signal or an unmodulated signal.
Refer to Outline Diagram for location of adjustments.
Bottom must be on chassis.

)R 'Y	BAND SELECTOR SETTING	RECEIVER DIAL SETTING	ADJUSTMENT
)	E	.54 MRz	L 3, top and bottom of T 2, T 3, T 4 for maximum output. Keep re- ducing the generator output to keep the output meter below 50 milli- watts.
	6	,54 Mis	Tune BFO to zero beat. Adjust knob so pointer aims straight up and tighten setscrew.
.)	В	1.3 MHz	C 107E and C 105E for maximum output as in Stap 1.

4.	Same as Step 3	0.6 MHz (30% mod.)	E	0.6 MHz	L 106B and L 103B for maximum output as in Step 1.
5.	Same as Step 3		E		Repeat steps 3 and 4 until no in- crease in output can be obtained on either adjustment.
6.	Same as Step 3	3.2 MHz (30% mod.)	D	3.2 MHs	C 107D and C 105D for maximum out- put as in Step 1.
7.	Same as Step 3	1.5 MHz (30% mod.)	D	1,5 MHz	L 105B and L 102B for maximum output as in Step 1.
8.	Same as Step 3		D		Repeat steps 6 and 7 until no in- crease in output can be obtained.
9.	Same as Step 3	8.0 MHz (30% mod.)	С	8.0 MHz	C 107C and C 105C for maximum out- put as in Step 1.
10.	Same as Step 3	3.8 MHz (30% mod.)	С	3.8 MHz	L 103A and L 106A for maximum out- put as in Step 1.
11.	Same as Step 3	·	С		Repeat steps 9 and 10 until no in- crease in output can be obtained.
12.	Same as Step 3	21 MHz (30% mod.)	В	21 MHz	C 107B and C 105B for maximum output as in Step 1.
13.	Same as Step 3	10 MHz (30% mod.)	В	10 MHz	L 102A and L 105A for maximum out- put as in Step 1.
14.	Same as Step 3		^		Repeat steps 12 and 13 until no in- crease in output can be obtained.
15.	Same as Step 3	50 MHz	A .	50 MHz	C 107A and C 105A for maximum output as in Step 1.
16.	Same as Step 3	25 MH:	٨	25 MHz	L 101 and L 104 for maximum output as in Step 1.
17.	Same as Step l		A		Repeat Steps 15 and 16 until no in- crease in output can be obtained.



NT PROCEDURE

ALIGHMENT PROCEDURE

1. Use an amplitude modulated generator covering 455 KHz to 54 HHz.

2. Connect the output mater across the speaker voice coil.

3. Use non-matallic alignment tools. GC #8606L or similar.

4. Use a stendard Elfa dummy antenna as shown.

5. VOLUME control near meximum clockwise.

BANDSPRADA control at 10.

AN-CW switch at AN
OFF-ANL switch in OFF position.

RP-GAIM at maximum unless noise exceeds 50 milliwatts with no signal or an unmodulated signal.

6. Refer to Outline Diagram for location of adjustments.


7. Bottom must be on chassis.

)R TY	BAND SELECTOR SETTING	RECEIVER DIAL SETTING	Adjustment
.)	E	.54 MHz	L 3, top and bottom of T 2, T 3, T 4 for maximum output. Keep re- ducing the generator output to keep the output meter below 50 milli- watts.
	E	.54 MHz	Tume BFO to zero beat. Adjust knob so pointer aims straight up and tighten setscrew.
.)	B	1.3 MHz	C 107E and C 105E for maximum output as in Step 1.


4,	Same as Step 3	0.6 MHz (30% mod.)	E	0.6 MHz	L 1068 and L 1038 for maximum out- put as in Step 1.
5.	Same as Step 3		E		Repeat steps 3 and 4 until no in- crease in output can be obtained on either adjustment.
6.	Same as Step 3	3.2 MHz (30% mod.)	D	3.2 MHz	C 107D and C 105D for maximum output as in Step 1.
7.	Same as Stap 3	1.5 MHz (30% mod.)	D	1.5 MHz	L 105B and L 102B for maximum out- put as in Step 1.
8.	Same as Step 3		D		Repeat steps 6 and 7 until no in- crease in output can be obtained.
9.	Same as Step 3	8.0 MHz (30% mod.)	С	8.0 MHz	C 107C and C 105C for maximum output as in Step 1.
10.	Same as Step 3	3.8 MHz (30% mod.)	С	3.8 MHz	L 103A and L 106A for maximum out- put as in Step 1.
11.	Same as Step 3		С		Repeat steps 9 and 10 until no in- crease in output can be obtained.
12.	Same as Step 3	21 MHz (30% mod.)	В	21 MHz	C 107B and C 105B for maximum output as in Step 1.
13.	Same as Step 3	10 MHz (30% mod.)	В	10 MHz	L 102A and L 105A for maximum out- put as in Step 1.
14.	Same as Step 3		٨		Repeat steps 12 and 13 until no in- crease in output can be obtained.
15.	Same as Step 3	50 MHz	A	50 MHz	C 107A and C 105A for maximum output as in Stap 1.
16.	Same as Step 3	25 MHz	*	25 MHz	L 101 and L 104 for maximum output as in Step 1.
17.	Same as Step 1		A		Repeat Steps 15 and 16 until no increase in output can be obtained.

FACTORY ASSEMBLED RF SUBASSEMBLY

<u> tem</u>	Description Description	
	Coils	
L 101	Coil antenna	1801 1601 032
L 102	Coil antenna	1801 1601 033
L 103	Coil antenna	1801 1601 034
L 104	Coil, oscillator	1801 1601 032
L 105	Coil, oscillator	1801 1601 035
L 106	Coil, oscillator	1801 1601 036
	Capacitors	
C 104	50 pF, ±10%, NPO, Disc ceramic	1501 5002 007
C 105 C 105	5×10-35 pF, mica trimmer	1573 3502 004
C 106	22 pF, ±10%, NPO, disc ceramic	1501 2202 007
C 107	5x10-35 pF, mica trimmer	1573 3502 004
C 110	0.0033 uF, ±10%, mica	1512 3304 003
C 111	0.0012 uF, ±5%, silver mica	1513 1204 008
C 112	500 pF, ±5%, silver mica	1513 5003 008
	Resistor and Switch	
R 101	1 K, ±20%, 1/2 W, comp	4701 1004 003
S 101	Bandswitch	5112 1601 037



SCHEMATIC DIAGRA



D1601001 Rev. C

RAM: R5K RECEIVER



ADDENDUM

UNIT:

AMECO R5 ALLWAVE RECEIVER


4210 1601 102 13 Dec 1967

This ADDENDUM should be kept with your Owner's Manual for the Model R-5 Allwave Receiver. The schematic diagram and printed circuit board diagram shown on this ADDENDUM reflect the latest changes in the R-5 Receiver.


Operation and Alignment Procedures have not been affected by the minor changes made to the R-5.

Changes are as follows:


- 1. Two pads, No. 26 and No. 27, were added to the printed circuit board.
- 2. Wire color designations were added or changed as necessary.
- 3. To improve sensitivity, all three IF amplifiers now use the common emitter circuit.



AG 150, REV A



SCHEMATIC DIAGRA



D1601001 Rev. C

M: R5 RECEIVER